

Withwave's SMA Conversion Adapter is used by compressing the mated portion of U.FL side onto the U.FL-R-SMT-1 portion.



■ Specification

Scope	Specification	Part No: MT420-SF18
Electrical	Impedance(Ohm)	50
	Operation Freq.(GHz)	DC to 6GHz
	VSWR (Max)	1.2 : 1
	Dielectric	PTFE
Mechanical	Center Contact	Beryllium copper with gold plated
	Body	Stainless steel & Beryllium with gold plated

*RoHS Compliant

■ Drawing

